



amazon basics A19 Smart LED Bulb User Manual

[Home](#) » [amazon basics](#) » amazon basics A19 Smart LED Bulb User Manual 

Contents

- [1 Amazon Basics A19 Smart LED Bulb](#)
- [2 Bulb Status Guide](#)
- [3 Alternative setup methods](#)
- [4 Cleaning and Maintenance](#)
- [5 FCC Compliance Statement](#)
- [6 Specifications](#)
- [7 Documents / Resources](#)

amazonbasics

Amazon Basics A19 Smart LED Bulb



Bulb Status Guide

Light bulb

- Flashes twice softly
- Flashes once softly, then remains soft white at full brightness
- Flashes five times quickly, then flashes twice softly in soft white

Status

- The bulb is ready for setup.
- The bulb is connected.
- Factory reset is complete, bulb is ready for setup again.

Set Up your Smart LED Light Bulb with Alexa

DANGER: Risk of fire, electric shock or death! Before replacing, make sure the light is powered off.

1. Download the latest version of the Alexa app from the app store and log in.

2. Screw in the smart LED light bulb and turn on the light. It will flash twice softly, indicating bulb is ready for setup
3. Open the Alexa app and tap “More” icon on the bottom-right of the screen, Tap “Add a Device”, and Select “Light” ->”Amazon Basics”, and choose your corresponding device. Then follow the on screen instructions. If prompted by the app, scan the barcode on the back page of the quick start guide.
(DON'T scan the barcode on packaging)

Alternative setup methods

Option 1

Add the device with the barcode on the light bulb, and follow these steps:

1. Keep the light bulb switched off and unscrew it from a socket.
2. Open the Alexa app and tap the More icon to add a device. Scan the barcode on the light bulb when prompted by app.
3. Screw the bulb back into socket and switch on the light again.

Follow the on-screen instructions in Alexa app to complete the setup

Option 2

If the barcode scan setup fails, select “DON'T HAVE A BARCODE?”, then follow the on-screen instructions to complete setup:

1. Make sure your device is powered on for at least 5 seconds, and then switch it off.
2. Use a light switch to quickly turn on and off the light for 5 At the 6th turn on, it will flash 5 times quickly, then flash twice softly.
3. Press NEXT on screen then follow the on-screen instructions to complete setup.

Use with Alexa Voice Commands

To use your bulb with Alexa, just say,

“Alexa, turn off first light”

Frequently Asked Questions

NOTICE: For more FAQ and more information, go to product detail page.

Problem 1

How do I reset the light bulb?

Solution 1

You can do a factory reset by deleting your device from the app. If you are not able to delete your device from Alexa app, alternatively: Use a light switch to quickly turn on and off the light for 5 times. At the 6th turn on, it will flash 5 times quickly, then flash twice softly, indicating you have successfully factory-reset your light bulb, and it is ready for setup again.

Problem 2

Amazon Alexa app cannot find or connect to the smart LED light bulb.

Solution 2

1. Check that your phone/tablet and the Alexa app have the latest software version.
2. Make sure that your phone/tablet and your smart LED light bulb are connected to the same 4 GHz Wi-Fi network. The bulb is not compatible with 5 GHz Wi-Fi network.
3. Check that your phone/tablet is within 30' (10 m) of your smart LED light
4. Restart your smart LED light To restart, power *off* the smart LED light bulb and power it back on.
5. If you have restarted your smart LED light bulb and it is still not working, reset your light bulb following the steps in Solution 1.

Problem 3

What if I lose the quick start guide, how can I set up my smart light bulb?

Solution 3

You can set up your device via two alternative setup methods. The instructions can be found in Section 2.1 "Alternate setup methods".

Problem 4

Error code (-1:-1:-1:-1) displays on the screen

Solution 4

Make sure your phone has Bluetooth turned on through out the entire setup process and the device you are trying to setup is in pairing mode. Restart your device by powering it off and on, and then set up again.

Important Safeguards

Read these instructions carefully and retain them for future use. If this bulb is passed to a third party, then these instructions must be included When using electrical bulbs, basic safety precautions should always be followed to reduce the risk of fire, electric shock, and/or injury to persons including the following:

- **DANGER:** Risk of fire, electric shock or death! Ensure the light is powered off from the light switch before changing bulb and before cleaning.
- **WARNING:** Take special precautions when working on heights, for example, while using a ladder. Use the right type of ladder and ensure it is structurally sound. Use the ladder in accordance with the manufacturer's instructions.
- **CAUTION:** SUITABLE FOR DAMP LOCATIONS. DO NOT USE OUTDOORS.
- **CAUTION:** NOT FOR USE IN TOTALLY ENCLOSED LUMINAIRES.
- **CAUTION:** THIS BULB IS NOT INTENDED FOR USE WITH EMERGENCY EXITS.
- **CAUTION:** DO NOT USE WITH STANDARD DIMMERS. Only use the control provided with or specified by these instructions to control this bulb. This bulb will not operate properly when connected to a standard (incandescent) dimmer or dimming control.
- **CAUTION:** The operation voltage of this bulb is 120 V~. It is not designed for universal voltage and cannot be used in 220 V~ environments.
 - The bulb should not be used if the diffuser is broken.
 - This bulb is intended for connection to E26 lampholders for outlet boxes or E26 lampholders provided in open luminaires.
 - This bulb is rated 120 V AC and must be connected to a suitable power source.
 - This bulb is intended for indoor dry or damp household use only.

- Do not attempt to disassemble, repair, or modify the bulb.

Before First Use

DANGER: Risk of suffocation!

Keep any packaging materials away from children and pets – these materials are a potential source of danger, e.g. suffocation.

- Remove all the packing materials.
- Check the bulb for transport damages.

Cleaning and Maintenance

WARNING: Risk of electric shock!

To prevent electric shock, turn off the power at circuit breaker or fuse before cleaning.

Cleaning

- To clean the smart LED light bulb, wipe with a soft, slightly damp cloth.
- Never use corrosive detergents, wire brushes, abrasive scourers, metal or sharp utensils to clean the bulb.

FCC – Supplier’s Declaration of Conformity

Unique Identifier

- **B09BFV9NRQ** Smart A19 LED Light Bulb, Dimmable Soft White, Works with Alexa
- **B09BFTR2GW** Smart A19 LED Light Bulb, Dimmable Soft White, Works with Alexa, 4-Pack
- **B09BFVYRMQ** Smart A19 LED Light Bulb, Tunable White, Works with Alexa
- **B09BFTLKNX** Smart A19 LED Light Bulb, Tunable White, Works with Alexa, 4-Pack
- **B09BFRLZZS** Smart A19 LED Light Bulb, Color Changing, Works with Alexa
- **B09BFSLWY2** Smart A19 LED Light Bulb, Color Changing, Works with Alexa, 4-Pack

Responsible Party
U.S. Contact Information
Telephone Number

Amazon.com Services LLC. 410 Terry Ave N. Seattle, WA 98109 USA

FCC Compliance Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
 - This device may not cause harmful interference, and
 - This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

FCC Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio / TV technician for help

RF Warning Statement:

The device has been evaluated to meet general RF exposure requirements. This device should be installed and operated with minimum distance of 8" (20 cm) between the radiator and your body.

Canada IC Notice

This device contains license-exempt transmitter(s)/ receiver(s) that comply with Innovation, Science and Economic Development Canada's licence exempt RSS(s). Operation is subject to the following two conditions:

- This device may not cause interference, and
- This device must accept any interference, including interference that may cause undesired operation of the device.

This equipment complies with Industry Canada radiation exposure limits set forth for an uncontrolled environment. This Class B digital apparatus complies with Canadian CAN ICES-003(8) / NMB-003(8) standard. This Class B digital apparatus complies with Canadian CAN ICES-005(8) / NMB-005(8) standard. This equipment complies with IC RSS-102 radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 8" (20 cm) between the radiator and any part of your body.

Specifications

Light type	Dimmable soft white
Model	11aSB-A800ST-Q1-WDN 11aSB-A800ST-Q1-WDN_4-Pack
Rated voltage	120 V AC 60 Hz
Rated current	104 mA
Rated power	7.5 W
Lumen output	800 lumens
Lifetime	15000 h
Correlated color temperature (CCT)	2700 K
Operating humidity	0 % - 85 % RH, non-condensing
Wi-Fi frequency	2.4 GHz
Wi-Fi protocol	802.11 b/g/n
Wi-Fi range	approx. 150 ft (50 m) - for areas without obstructions
Net weight	approx. 0.16 lbs (72 g)
Dimensions	approx. 2.36 x 4.21" (6 x 10.7 cm)

Light type	Tunable white
Model	11aSB-A800ST-Q1-WZN 11aSB-A800ST-Q1-WZN_4-Pack
Rated voltage	120 V AC 60 Hz
Rated current	104 mA
Rated power	7.5 W
Lumen output	800 lumens
Lifetime	15000 h
Correlated color temperature (CCT)	2200 K - 6500 K
Operating humidity	0 % - 85 % RH, non-condensing
Wi-Fi frequency	2.4 GHz
Wi-Fi protocol	802.11 b/g/n

Wi-Fi range	approx. 150 ft (50 m) - for areas without obstructions
Net weight	approx. 0.16 lbs (73 g)
Dimensions	approx. 2.36 x 4.21" (6 x 10.7 cm)
Light type	Color changing
Model	11aSB-A800ST-Q1-WGN 11aSB-A800ST-Q1-WGN_4-Pack
Rated voltage	120 V AC 60 Hz
Rated current	104 mA
Rated power	7.5 W
Lumen output	800 lumens
Lifetime	15000 h
Correlated color temperature (CCT)	2200 K - 6500 K
Operating humidity	0 % - 85 % RH, non-condensing
Wi-Fi frequency	2.4 GHz
Wi-Fi protocol	802.11 b/g/n
Wi-Fi range	approx. 150 ft (50 m) - for areas without obstructions
Net weight	approx. 0.17 lbs (76 g)
Dimensions	approx. 2.36 x 4.21" (6 x 10.7 cm)

Feedback and Help

We would love to hear your feedback. To ensure we are providing the best customer experience possible, please consider writing a customer review.

-  [amazon.com/review/ review-your-purchases#](https://www.amazon.com/review/review-your-purchases#)

If you need help with your Amazon Basics product, please use the website or number below.

-  [amazon.com/gp/help/customer/ contact-us](https://www.amazon.com/gp/help/customer/contact-us)
-  +1 877-485-0385

MADE IN CHINA
vol-06/22

Documents / Resources

amazon basics



Smart LED Light Bulb
Ampeola LED intelligente
Bombilla LED inteligente
B09BFPY9RHQ, B09BFTK2GW,
B09BFPY9RMQ, B09BFTLKNX,
B09BFLZ2S, B09BFLWY2

EN	Page 2
FR	Page 18
ES	Página 34

[amazon basics A19 Smart LED Bulb](#) [pdf] User Manual A19 Smart LED Bulb, A19, Smart LED Bulb, LED Bulb, Bulb